

KXT 816 / 1232 System Programming

Extension Port Assignment

Select the port being used for VM. Set the extension group to 8 for each extension to be in the VM extension group.

Jack	EXT	Name	X D P	E X G	Doorphone Day Night	LCS Mode	FWD N/A Time	Cordless PITS	
01-1	[101]	[ALEX] N	[1]	YYYY	YYYY	Stop Rec	[00]	N
01-2	[201]	[] -	[1]	NNNN	NNNN		[00]	-
02-1	[102]	[MIKE] N	[1]	NNNN	NNNN	Stop Rec	[00]	N
02-2	[202]	[] -	[1]	NNNN	NNNN		[00]	-
03-1	[103]	[] N	[1]	NNNN	NNNN	Stop Rec	[00]	N
03-2	[203]	[] -	[1]	NNNN	NNNN		[00]	-
04-1	[104]	[] N	[1]	NNNN	NNNN	Stop Rec	[00]	N
04-2	[204]	[] -	[1]	NNNN	NNNN		[00]	-
05-1	[105]	[] Y	[1]	NNNN	NNNN	Stop Rec	[00]	N
05-2	[200]	[UM ONE] -	[8]	NNNN	NNNN		[00]	-
06-1	[106]	[] Y	[1]	NNNN	NNNN	Stop Rec	[00]	N
06-2	[206]	[UM TWO] -	[8]	NNNN	NNNN		[00]	-
07-1	[107]	[] N	[1]	NNNN	NNNN	Stop Rec	[00]	N
07-2	[207]	[] -	[1]	NNNN	NNNN		[00]	-
08-1	[108]	[] N	[1]	NNNN	NNNN	Stop Rec	[00]	N
08-2	[208]	[] -	[1]	NNNN	NNNN		[00]	-

Turn the XDP to Y for VM ports so the analog port may be used. Name the Voice Mail Extensions under Name.

Extension Group for VM

Set Extension Group 8 to V for voice mail.

Miscellaneous		On-line:ROM[P211D]			Empty			
Expansion Card Type	<Master> -> X01	EXP1	EXP2	EXP3				
	<Slave> -> -----	EXT1	EXT2	EXT2				
Local Access ->	Priority = 1 2 3 4 5 6 7 8							
	TRG No. = [1] [2] [3] [4] [5] [6] [7] [8]							
Call Hunting ->	EXG No. = 1 2 3 4 5 6 7 8							
	D D D D D D D U							
SPD IRS Override	-> Disable	HOTEL FEATURE	-> Off					
CO Auto-Hold by Push	DSS-Key -> Enable	DID SELECT	-> Transfer Table					
	CO-Key -> Disable	Off-Hook Monitor	-> Enable					
Adjust Time	-> [01:00] AM							
PBX Code	-> []	Caller ID	Extension					
		EXP 1	Not Stored					
		EXP 2	Not Stored					
		EXP 3	Not Stored					
		EXP 4	Not Stored					

System Timers

```

D:\kxt_tool\E1232A.exe
Timer                                     Off-line                               KK-ID1232 Master
Name <Range>                             Data
Hold Recall Time                         < 0 - 240 sec >-> [060]
Transfer Recall Time                     < 0 - 48 rings >-> [04]
No Answer Time                           < 1 - 12 rings >-> [05]
Intercept Time                           < 3 - 48 rings >-> [06]
Pickup Dial Waiting Time                 < 1 - 5 sec >-> [1]
CO Call Duration Time                    < 1 - 64 min >-> [10]
CO-CO Call Duration Time                 < 1 - 64 min >-> [10]
1st Digit Time                           < 5 - 120 sec >-> [010]
Inter Digit Time                         < 5 - 30 sec >-> [10]
Automatic Redial Repeat Times            < 0 - 15 Attempts >-> [00]
Automatic Redial Interval Time           < 30 - 1200 sec >-> [004]
CO Dial Starting Time                    < 0 - 4000 nsec >-> [05]
Call Duration Count Start Time           < 0 - 60 sec >-> [00]
DISA Delayed Answer Time                 < 0 - 6 rings >-> [1]
DISA Prolong Time                        < 0 - 7 min >-> [3]
MW Interval Time                         < 0 - 64 sec >-> [00]
Toned Reminder                           < 30 - 240 sec >-> [030]
DISA Auto Answer Wait Time               < 1 - 5 sec >-> [1]
Call Park Recall Time                    < 0 - 48 rings >-> [12]
TIE First/Inter Digit Time               < 3 - 30 sec >-> [35]
Enter numeric code
1 2 3 4 HELP 5 6 7 8 SAVE 9 EXIT
  
```

Change No Answer Time from 12 to 5

This timer MUST be changed and can't be the same number of rings that the Innovator ring no answer field is set for (default 4). The Panasonic system must be 1 ring more that the voicemail or you could have looping problems.

Set DTMF Digits

```

D:\kxt_tool\E1232A.exe
Voice Mail                               On-line:ROM(P211D)                       Empty
Extension Status
Ringback Tone                            [1 ]
Busy Tone                                 [2 ]
Reorder Tone                              [3 ]
DND Tone                                  [4 ]
Extension Answer                          [5 ]
Extension Disconnect                       [#9 ]
Confirmation Tone                         [9 ]
PVD to UM Ringback Tone                   [6 ]
PVD to UM Busy Tone                       [7 ]
PVD to Extension Ringback Tone            [8 ]
Voice Mail Command
Leave Message                              [#H ]
Get Message                               [#H ]
AA Service                                 [ ]
UM Service                                 [#6 ]
Enter numeric code
1 2 3 4 HELP 5 6 7 8 SAVE 9 EXIT
  
```

Clear AA Service field

Set Timers in Additional Functions (field 990)

Additional Function	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
FNC																
SYS01	0	1	1	0	0	0	1	0	1	1	0	0	0	0	0	1
SYS02	1	1	1	0	0	1	1	0	0	0	1	0	1	1	0	0
SYS03	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
SYS04	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
SYS05	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS06	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS07	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS08	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS09	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS10	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS11	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
SYS12	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
COS1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS2	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS3	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS4	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS5	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS6	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS7	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0
COS8	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0

Hit spacebar to select parameter
 [1] [2] [3] [4] HELP [5] [6] [7] SAVE [8] EXIT

SYS01

Set 15, to 1 Message lamp turn off by voicemail

Set 14, to 1, 13 to 0

Set 12, to 0, 11 to 0.

Set CO to DIL to VM for each trunk group that you wish answered as auto attendant

CO No	C O	T R I D	D I T P	D I T P	C I	CPC Detection Mode	DIL 1:1 EXT No	R E U	DIL 1:1 Lunch Group	Break Group
01	[1]	[1]	D	80	10	N	400ms Disable	EXT(200)	Disable	Reg. [] []
02	Y	[2]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
03	Y	[3]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
04	Y	[4]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
05	Y	[5]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
06	Y	[6]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
07	Y	[7]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
08	Y	[8]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
09	Y	[9]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
10	Y	[0]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
11	Y	[1]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []
12	Y	[2]	D	80	10	N	400ms Disable	Disable	Disable	Reg. [] []

Hit spacebar to select parameter
 [1] [2] COPY [3] [4] HELP [5] P-PAGE [6] N-PAGE [7] SAVE [8] EXIT

Additional Programming

Voice Mail Transfer Button

From workstation:

Program

99

Press a vacant button on telephone

8

Pilot Extension Number